

Specifications



Eaton 073302

Eaton Moeller® series A-PKZ0 Shunt release (for power circuit breaker), 230 V 50 Hz, Standard voltage, AC, Screw terminals, For use with: Shunt release PKZ0(4), PKE

General specifications

PRODUCT NAME	Eaton Moeller® series A-PKZ0 Accessory Shunt release
CATALOG NUMBER	073302
MODEL CODE	+A-PKZ0(230V50HZ)
EAN	4015080733027
PRODUCT LENGTH/DEPTH	68 mm
PRODUCT HEIGHT	90 mm
PRODUCT WIDTH	24 mm
PRODUCT WEIGHT	0.1 kg
CERTIFICATIONS	CSA Class No.: 3211-05 CSA File No.: 165628 UL 508 CSA-C22.2 No. 14 IEC 60947-4-1 CE marking UL Category Control No.: NLRV UL File No.: E36332 UL Listed CSA certified
GLOBAL CATALOG	073302

Product specifications

ELECTRIC CONNECTION TYPE	Screw connection
UNDELAYED SHORT-CIRCUIT RELEASE - MAX	0 A
UNDELAYED SHORT-CIRCUIT RELEASE - MIN	0 A
NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	0
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	230 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	230 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	0 V
VOLTAGE TYPE	AC
SUITABLE FOR	Motor safety switch
POWER CONSUMPTION	0.5 W

Resources

BROCHURES	eaton-motor-starters-system-xstart-brochure-br03407001en-en-us.pdf
CATALOGS	Product Range Catalog Switching and protecting motors eaton-product-overview-for-machinery-catalogue-ca08103003zen-en-us.pdf
DECLARATIONS OF CONFORMITY	eaton-accessory-declaration-of-conformity-uk251155en.pdf eaton-accessory-declaration-of-conformity-eu250672en.pdf
DRAWINGS	eaton-manual-motor-starters-release-u-pkz0-accessory-dimensions.eps eaton-manual-motor-starters-shunt-releases-u-pkz0-accessory-3d-drawing.eps eaton-manual-motor-starters-release-u-pkz0-accessory-3d-drawing.eps
ECAD MODEL	ETN.073302.edz
INSTALLATION INSTRUCTIONS	IL03407011Z.pdf IL03402034Z
INSTALLATION VIDEOS	WIN-WIN with push-in technology
MCAD MODEL	DA-CS-a_pkz DA-CD-a_pkz
SALES NOTES	eaton-link-module-for-motor-starters-pkz-flyer-fl034003en-en-us.pdf
WIRING DIAGRAMS	eaton-manual-motor-starters-release-a-pkz0-shunt-release-wiring-diagram.eps

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
DATE:



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

